(Continued From Drawing PX 9-105)

All Continuity measurements are made with Static Tester set at 7-11-0.

Static tests are to be made with all tubes and plug-in units (including the transformer plugs in units) removed. Before plugging in the D.C. cables, a resistance measurement should be made from every voltage terminal to every other to determine shorts; this should ensure against damage in the cases listed. Static tests are made with all cables removed except the D.C. cables.

TO	(A)
1.	0
2.	20
3.	58
4.	115
5.	140
6.	175
7.	235
8.	1 1
9.	-200

10.	-255	
11.	-275	
12.	-290	
13.	150	
14.	—	
15.	-233	
16.	-215	
17.	-205	
18.	50	

TO	(B)
1.	1
2.	-235
3.	-230
4.	-190
5.	95
6.	230
7.	-235
8.	-235
9.	-150

10.	-235	
11.	-230	
12.	0	clear
13.	1	
14.	1	
15.	-215	
16.	-210	
17.	-210	
18.	110	ring

For Resistance Measurements

Between Pins on D.C. Plugs

See PX-9-102.

Legend

Refers to Static Panel Tester (Dx-9-102)

A5	Refers to position of reference voltage switches A, B, or C.
7-11-0	Refers to position of switches (7, 11, and 0 respectively).
50	Setting of Static tube voltmeter.







Pin / Tube	1	2	3	4	5	6	7	8	9	10	11	12
V1-1	SG-6 ---- Short	To ground ---- Short	To 1 ---- 0 M	----	----	----	----	----	----	----	----	----
V1-2 V1-3	SG-4 ---- Short	To ground ---- Short	----	----	----	----	----	----	----	----	----	----
V1-4	SG-2 ---- Short	Ground ---- Short	----	----	----	----	----	----	----	----	----	----
V1-5	SG-9 ---- Short	Ground ---- Short	----	----	----	----	----	----	----	----	----	----
V1-6	SG-10 ---- Short	Ground ---- Short	----	----	----	----	----	----	----	----	----	----
V1-7	SG-11 ---- Short	Ground ---- Short	----	----	----	----	----	----	----	----	----	----
SC	----	----	----	----	Ground ---- Short 1 Ohm	----	LS3-8 ---- 6.8K	See Note A	See Note B	See Note B	Ground ---- Short	See Note A
SU	----	ABC GUTY, 27 A to K 30 K.2K	----	----	----	----	----	----	----	----	----	1K7-3 ----
SV	----	----	----	----	----	----	----	----	----	----	LS3-9 ---- 1.2K	----
V2-1	----	A-1 1-7-0 1.0	MG3-3 ---- Short	A-1 1-7-0 290	A-9 1-7-0 290	----	SM3-1 ---- Short	MG2-2 ---- Short	SM3-3 ---- Short	SM3-4 ---- Short	----	----
	----	----	----	----	----	----	----	A-9 1-7-0 275	----	A-9 1-7-0 275	----	----
V2-2, V2-3	L-M5-3 ---- Short	A-1 1-7-0 1.0	----	A-1 1-7-0 290	A-9 1-7-0 290	----	SM3-11 ---- Short	MG1-12 ---- Short	MG2-1 ---- Short	MG2-2 ---- Short	----	----
	----	----	----	----	----	----	----	A-9 1-7-0 145	----	A-9 1-7-0 275	----	----
V2-4	K-M7-3 ---- Short	A-1 1-7-0 120	----	A-1 1-7-0 290	A-2 1-7-0 290	----	SM3-9 ---- Short	MG3-10 ---- Short	MG3-5 ---- Short	MG3-6 ---- Short	----	----
	----	----	----	----	----	----	----	A-9 1-7-0 145	----	A-9 1-7-0 275	----	----
V2-5	J-M7-3 ---- Short	A-1 11-7-0 1	----	A-1 1-7-0 290	A-9 1-7-0 290	----	SM3-7 ---- Short	MG3-10 ---- Short	MG3-5 ---- Short	MG3-6 ---- Short	----	----
	----	----	----	----	----	----	----	A-9 1-7-0 145	----	A-9 1-7-0 275	----	----
V2-6	G-M7-3 ---- Short	A-1 1-7-0 1.0	----	A-1 1-7-0 290	A-9 1-7-0 290	----	SM3-7 ---- Short	MG3-6 ---- Short	SM3-3 ---- Short	MG3-4 ---- Short	----	----
	----	----	----	----	----	----	----	A-9 1-7-0 145	----	A-9 1-7-0 275	----	----
V2-7	E-M7-3 ---- Short	A-1 1-7-0 120	----	A-1 1-7-0 290	A-2 1-7-0 290	----	SM3-7 ---- Short	MG3-6 ---- Short	MG3-3 ---- Short	MG3-4 ---- Short	----	----
	----	----	----	----	----	----	----	A-9 1-7-0 145	----	A-9 1-7-0 275	----	----
	A-1 1-7-0 110	----	A-1 1-7-0 40	----	MG3-9 ---- Short	MG3-9 ---- Short	MG3-1 ---- Short	SM3-2 ---- Short	A-2 1-7-0 20	A-1 1-7-0 110	A-2 1-7-0 150	A-2 1-7-0
	----	----	----	----	----	MG3-9 ---- Short	----	A-1 1-7-0 75	----	----	----	----
V2-8	A-1 1-7-0 75	A-1 1-7-0 75	A-1 1-7-0 40	A-1 1-7-0 90	MG3-7 ---- Short	MG3-7 ---- Short	MG3-7 ---- Short	MG3-10 ---- Short	A-2 1-7-0 20	A-1 1-7-0 110	A-1 1-7-0 150	MG1-12 ---- Short
	----	----	----	----	----	----	----	A-1 1-7-0 =130	----	----	----	----
V2-9	A-1 1-7-0 275	A-1 1-7-0 75	A-1 1-7-0 ----	A-1 1-7-0 ----	MG3-7 ---- Short	----	MG3-7 ---- Short	MG3-6 ---- Short	A-1 1-7-0 20	Ground ---- Short	A-1 1-7-0 150	SM3-12 ---- Short

Note A. With Operation Switch Set For Cont. or 1 Add:-

MG 12 to K 26-1.....7K
MG 6 to K 26-1.....Open

With Operation Switch Set for 1 Pulse:-

MG 12 to K 26-1.....Open
MG 6 to K 26-1.....7K

Note B. With Operation Switch Set For Cont.

SG 9 to 10.....Open

With Operation Switch Set For 1 Add or 1 Pulse

SG 9 to 10.....Short

Pin / Tube	1	2	3	4	5	6	7	8	9	10	11	12
V3-1	G47-7 ---- Short	J47-7 ---- Short	J47-7 ---- Short	J47-7 ---- Short	K47-7 ---- Short	L47-7 ---- Short	J47-7 ---- Short	J48-2 ---- Short	K23-7 ---- Short	K22-2 ---- Short	K21-7 ---- Short	K22-7 ---- Short
V3-2	----	----	L23-7 ---- Short	L22-8 ---- Short	K22-7 ---- Short	L23-7 ---- Short	----	K23-2 ---- Short	K23-7 ---- Short	K22-2 ---- Short	K22-7 ---- Short	K22-2 ---- Short
	K-6-7 ---- Short	K22-2 ---- Short	----	----	----	----	----	----	----	----	----	----
V3-4	----	----	----	----	L23-7 ---- Short	L23-7 ---- Short	----	----	K23-7 ---- Short	K25-6 ---- Short	K23-7 ---- Short	K25-6 ---- Short
	----	----	----	----	----	----	----	----	----	K23-3 ---- Short	K23-1 ---- Short	K23-2 ---- Short
V3-5	SM3-9 ---- Short	SM3-10 ---- Short	G1-7 ---- Short	----	----	----	----	K-10 ---- Short	K22-9 ---- Short	K22-10 ---- Short	SG1-7 ---- Short	SG10-10 ---- Short

ELECTRICAL ENGINEERS
DESIGNERS OF INDUSTRIAL CONTROL
1004 - 2nd AVENUE
SEATTLE 4, WASHINGTON